

Beam 3

PENDANT MOUNT - INDIRECT REGULAR LIT CORNER PATTERNS



* Please see page 2 for example on how to specify various right angle patterns.





Project _ **Type Notes**

TOP VIEW - Open Shape Corner Pattern TOP VIEW - Rectangle Corner Pattern

IMPORTANT! - all corner patterns must be submitted with drawings indicating dimensions and angles degree.

Refer to axislighting.com for complete fixture details, IES files, and installation instructions





Ordering Guide

TB3ILEDPAT													
PRODUCT ID		PATTERNS AND LENGTH (SELECT ONE)		LUMENS/FT INDIRECT		CRI		COLOUR TEMP.		SHIELDING INDIRECT		SPECIFY LENGTH	
TB3ILEDPAT	Beam 3 Indirect	R(LxL) U(LxLxL)	square shape (length) rectangular shape (length) U shape (length) L shape (length)		300 lm/ft - min 1200 lm/ft - max	80	80 CRI	35	3000 K 3500 K 4000 K		spotless lens batwing		nominal exact
				Outputs between listed min and max are available.									


FINISH		VOLTAGE		DRIVER		CIRCUITS		MOUNTING/SUSPENSION			BATTERY (OPT.)	
W	white	120	120V	DP	dimming (0-10V) 1%	1	1 circuit	CA(#)	drywall+cable length (36"std)	B(#)	battery pack	
BLK	black*	277	277V			2	2 circuits	CT9(#)	TB/TG 9/16+cable length (36" std.)		4' sections	
AP	aluminum paint*	347	347V			+E(#)	emergency circuit*	CT15(#)	TB/TG15/16+cable length (36" std.)			
		UNV	universal					CTS(#)	screw slot+cable length (36" std.)			
								SA(#)	drywall+stem length>48 (18"std)			
								CASL(#)	drywall cable sloped ceiling			
								SASL(#)	drywall stem sloped ceiling			
*Additional 5 working days required.						*Specify quantity		See Mountin	ng kit guide for full specification code. ntity	Requires 120V or 277V Please consult factory		




How to Specify 90 degree Corners and Patterns

Example

Defining R - Rectangular shape




Defining L shape




Note: The first number will always define the width, the second - the length.

Defining U shape



Note: The first number will always define the right arm length, the second - the width, and the third the left arm length.

Defining S - Square shape



Note: The number will define the width. (All sides are the same length).

